

Item	Details
Model	M6
Hotkeys for BIOS Setup & Boot Menu	Press Delete to enter BIOS Setup; Press F11 to open Boot Menu
CPU	AMD Ryzen 7 3700U
Cooling System & Fan Noise	Air cooling. Max CPU temperature: 85°C; Fan speed: 2500RPM; Max fan noise: 55dB. Test environment: 28°C with good ventilation
TDP	12W - 35W
Process Technology	12nm
Memory Slots	2×DDR4 260Pin SODIMM, maximum 32GB RAM, max memory frequency 2400MHz
Audio Chip	Realtek ALC 662 (Stereo)
I/O Ports	4×USB3.0 Type-A + 1×USB3.1 Gen1 Type-C
DC Power Port	1 port, compatible with 5.5*2.1MM DC power plug
Audio Jack	1×3.5mm combo audio jack for 4-pin headsets with microphone
Ethernet Port	1×RJ45 Realtek RTL8168/8111 Gigabit LAN (1000Mbps)
Antenna Interfaces	2 ports for external Wi-Fi module antennas
Video Output Ports	1×HDMI 1.4: 4K@30Hz 1×DP 1.2: 4K@60Hz
Graphics	AMD Radeon RX Vega 10 Graphics, 2GB shared video memory
Storage Slots	1×M.2 M Key 2280 PCIe3.0 x4 / SATA, supports NVMe & SATA SSD No MSATA slot 1×SATA3.0 bay for 2.5-inch HDD / SSD

Item	Details
Expansion Slot	1×M.2 2230 slot. Pre-installed Realtek 8821AE (Bluetooth 4.0). Optional Wi-Fi 6 + Bluetooth 5.2 module
Power Supply	Standard: 12V 6A; Compatible with 19V 4.74A power adapter
Extra Functions	TPM 2.0 support, auto power-on (configured in BIOS), Wake-on-LAN (works under all power-off modes), PXE boot
Supported OS	Windows 10, Windows 11, Linux
Installation Method	Standard desktop stand included; compatible with VESA wall mount bracket
Operating Temperature	0°C - 60°C
Mainboard Size	110mm × 100mm
Chassis Dimension	127mm × 127mm × 53mm
Net Weight	1.3KG
Chassis Material	Aluminum Alloy
Improvement Suggestions	N/A